

## Z-Wave Protocol Implementation Conformance Statement

### Smart Dimmer Switch

#### General Information

<b>Product Identifier:</b>	MS11Z
<b>Brand Name:</b>	Minoston
<b>Product Version:</b>	HW: 1 FW: 20.15
<b>Z-Wave Certification #:</b>	ZC10-19066552

#### Product Features

<b>Color</b>	White
<b>Electric Load Type</b>	Dimmable LED Incandescent
<b>Switch Load Capacity Watts</b>	500W
<b>Switch Type</b>	Push Button

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xFF04
<b>Z-Wave Product Type:</b>	0xFF00
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.51.06
<b>Z-Wave Library Type:</b>	Routing Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Dimmer Switch

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 5                    Z-Wave Plus Lifeline

**Supported Command Classes (10):**

Association Group Info	Association V2
Basic	Device Reset Locally
Manufacturer Specific V2	Powerlevel
Switch All	Switch Multilevel
Version V2	Z-Wave Plus Info V2