

Z-Wave Protocol Implementation Conformance Statement

Door/Window Sensor 7

General Information

Product Identifier:	ZWA008-C
Brand Name:	Aeotec
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-19066568

Product Features

Battery Quantity	1
Battery Type	1/AA
Color	White
Firmware Updatable	Updatable by Consumer by RF
Sensors	Open/Closed (Binary)
Supported Notification Types	Access Control Home Security Power Management

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Door/Window Sensor 7

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0007
Z-Wave Product Type:	0x0000
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.81.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5	Z-Wave Plus Lifeline
2 / 5	Control devices when magnet or external dry contacts trips
3 / 5	Sends our alarm message when magnet controlled or external dry sensor trips.
4 / 5	Sends alarm messages when tamper is tripped

Supported Command Classes (18):

Association Group Info	Association V2
Battery	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Notification V8
Powerlevel	Security S2
Sensor Binary V2	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2