



Z-Wave Protocol Implementation Conformance Statement

Gesture Controller

General Information

Product Identifier: FGGC-001
Brand Name: FIBARO
Product Version: HW: 1 FW: 3.03:03.11
Z-Wave Certification #: ZC10-19076656

Product Features

Battery Quantity 4
Battery Type 1,5V AA
Color White

Z-Wave Product Information

Supports Z-Wave Beaming Technology? No
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? Yes
Supports Security S2? No
SmartStart Compatible? No

Z-Wave Technical Information

Z-Wave Frequency: China
Z-Wave Product ID: 0x8000
Z-Wave Product Type: 0x0D01
Z-Wave Hardware Platform: ZM5101
Z-Wave Development Kit Version: 6.51.07
Z-Wave Library Type: Enhanced 232 Slave
Z-Wave Device Type / Role Type: Wall Controller / Portable Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Gesture Controller

Association Group Information

Group # / Max Description

Nodes

1 / 1	“Lifeline” reports the device status and allows for assigning single device only (main controller by default).
2 / 5	“Flick UP” is assigned to moving the hand up over the panel (sends Basic Set command frames).
3 / 5	“Flick DOWN” is assigned to moving the hand down over the panel (sends Basic Set command frames).
4 / 5	“Flick LEFT” is assigned to moving the hand from the right to the left side of the panel (sends Basic Set command frames).
5 / 5	“Flick RIGHT” is assigned to moving the hand from the left to the right side of the panel (sends Basic Set command frames) .
6 / 5	“Circular AirWheel” is assigned to circular move of the hand clockwise or counter-clockwise over the panel (sends Switch Multilevel Start/Stop Level Change command frames).

Supported Command Classes (15):

Command Class Association Group Info	Command Class Association V2
Command Class Battery	Command Class Central Scene V2
Command Class Configuration	Command Class CRC16 Encap
Command Class Device Reset Locally	Command Class Firmware Update Md V3
Command Class Manufacturer Specific V2	Command Class Multi Channel Association V3
Command Class Powerlevel	Command Class Security
Command Class Version V2	Command Class Wake Up V2
Command Class Z-Wave+ Info V2	

Controlled Command Classes (3):

Command Class Basic	Command Class Central Scene V2
Command Class CRC16 Encap	