

## Z-Wave Protocol Implementation Conformance Statement

### Gesture Controller

#### General Information

<b>Product Identifier:</b>	FGGC-001
<b>Brand Name:</b>	FIBARO
<b>Product Version:</b>	HW: 1 FW: 3.03:03.11
<b>Z-Wave Certification #:</b>	ZC10-19076665

#### Product Features

<b>Battery Quantity</b>	4
<b>Battery Type</b>	1,5V AA
<b>Color</b>	White

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	Japan
<b>Z-Wave Product ID:</b>	0xA000
<b>Z-Wave Product Type:</b>	0x0D01
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.51.07
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Wall Controller / Portable Slave

#### Association Group Information

<b>Group # / Max</b>	<b>Description</b>
<b>Nodes</b>	

# Z-Wave Protocol Implementation Conformance Statement

## (Continued)

### Gesture Controller

- 2 / 5 "Flick UP" is assigned to moving the hand up over the panel (sends Basic Set command frames).
- 3 / 5 "Flick DOWN" is assigned to moving the hand down over the panel (sends Basic Set command frames).
- 4 / 5 "Flick LEFT" is assigned to moving the hand from the right to the left side of the panel (sends Basic Set command frames).
- 5 / 5 "Flick RIGHT" is assigned to moving the hand from the left to the right side of the panel (sends Basic Set command frames) .
- 6 / 5 "Circular AirWheel" is assigned to circular move of the hand clockwise or counter-clockwise over the panel (sends Switch Multilevel Start/Stop Level Change command frames).

### Supported Command Classes (15):

Association Group Info	Association V2
Battery	Central Scene V2
Configuration	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific V2	Multi-Channel Association V3
Powerlevel	Security S0
Version V2	Wake Up V2
Z-Wave Plus Info V2	

### Controlled Command Classes (3):

Basic	Central Scene V2
CRC16 Encapsulation	