

Z-Wave Protocol Implementation Conformance Statement

Doorbell Gateway

General Information

Product Identifier:	D1
Brand Name:	Starvedia
Product Version:	HW: 0 FW: 6.04:04.00:00.00:22.00
Z-Wave Certification #:	ZC10-19076652

Product Features

Communications Connections	Ethernet (Wireless/WiFi)
Communications Protocol	Manufacturer Proprietary Protocol
Firmware Updatable	Updatable by Consumer via Internet
Sensors	Humidity Luminance Power
Supported Notification Types	CO Alarm CO2 Alarm Heat Alarm Smoke Alarm Water Alarm
Switch Load Capacity Current	1.5
Switch Load Capacity Volt-Ampere	20
Switch Load Capacity Watts	7.5

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control, S2 Authenticated, S2 Unauthenticated

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Doorbell Gateway

Z-Wave Technical Information

Z-Wave Frequency:	Australia / New Zealand
Z-Wave Product ID:	0x0009
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.03
Z-Wave Library Type:	Static Controller
Z-Wave Device Type / Role Type:	Central Controller / Central Static Controller

Association Group Information

Group # / Max **Description**

Nodes

1 / 1 Z-Wave Plus Lifeline, report Device Reset Locally when reset.

Supported Command Classes (15):

Application Status	Association Group Info
Association V2	CRC16 Encapsulation
Device Reset Locally	Inclusion Controller
Manufacturer Specific	Manufacturer Specific V2
Powerlevel	Security S0
Security S2	Supervision
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (19):

Association V2	Basic
Battery	CRC16 Encapsulation
Door Lock	Manufacturer Specific V2
Meter	Multi-Channel Association V3
Multi-Channel V4	Notification V4
Security S0	Security S2
Sensor Binary V2	Sensor Multilevel
Switch Binary	Switch Color
Switch Multilevel V2	Version V2
Wake Up V2	