

## Z-Wave Protocol Implementation Conformance Statement

### Dwelo Controller

#### General Information

<b>Product Identifier:</b>	DGW-101-2
<b>Brand Name:</b>	Dwelo
<b>Product Version:</b>	HW: 1 FW: 6.04:02.81:01.00:01.00
<b>Z-Wave Certification #:</b>	ZC10-19086716

#### Product Features

<b>Communications Connections</b>	Ethernet (Wired)
<b>Sensors</b>	Air Temperature Humidity
<b>Supported Notification Types</b>	Access Control Smoke Alarm Water Alarm
<b>Color</b>	White
<b>Z-Wave Scene Type</b>	Central Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control, S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0002
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5304
<b>Z-Wave Development Kit Version:</b>	6.81.04

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Dwelo Controller

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1                    Z-Wave Plus Lifeline

**Supported Command Classes (24):**

Application Status	Association Group Information V3
Association V2	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V5
Inclusion Controller	Manufacturer Specific V2
Network Management Basic V2	Network Management Inclusion V3
Network Management Installation and Maintenance	Network Management Proxy V2
Node Provisioning	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
Version V2	Z/IP Gateway
Z/IP Portal	Z/IP V3
Z/IP-ND	Z-Wave Plus Info V2

**Controlled Command Classes (32):**

Association Group Information V3	Association V2
Barrier Operator	Basic V2
Battery	Central Scene V3
Configuration V3	CRC16 Encapsulation
Door Lock V3	Manufacturer Specific V2
Meter Table Monitor	Meter V3
Multi-Channel Association V3	Multi-Channel V4
No Operation	Node Naming
Notification V8	Security S0
Security S2	Sensor Alarm
Sensor Multilevel V11	Switch Binary V2
Switch Color V3	Switch Multilevel V4
Thermostat Fan Mode V4	Thermostat Fan State V2
Thermostat Mode V3	Thermostat Operating State V2
Thermostat Setpoint V3	User Code
Version V2	Wake Up V2