

## Z-Wave Protocol Implementation Conformance Statement

### Z-Wave Plus thermostat

#### General Information

<b>Product Identifier:</b>	CT200-G1
<b>Brand Name:</b>	Radio Thermostat Company of America
<b>Product Version:</b>	HW: 255 FW: 12.06
<b>Z-Wave Certification #:</b>	ZC10-19086714

#### Product Features

<b>Battery Quantity</b>	4
<b>Battery Type</b>	AA Alkaline
<b>Thermostat Modes</b>	Auto Auxiliary/Emergency Heat Cool Furnace Heat
<b>Thermostat Power Source</b>	Battery External Transformer Mains powered (120V/240V)
<b>Sensors</b>	Air Temperature Humidity
<b>Thermostat HVAC Systems Supported</b>	Dual Fuel Heat Only Heat Pump Multi Stage Single Stage Universal

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Z-Wave Plus thermostat

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0024
<b>Z-Wave Product Type:</b>	0xC801
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Thermostat - HVAC / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 2                Z-Wave Plus Lifeline

**Supported Command Classes (20):**

Association Group Info	Association V2
Basic	Battery
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Powerlevel	Security S2
Sensor Multilevel V6	Supervision
Thermostat Fan Mode	Thermostat Fan State
Thermostat Mode V2	Thermostat Operating State V2
Thermostat Setpoint V2	Transport Service V2
Version V2	Z-Wave Plus Info V2