

Z-Wave Protocol Implementation Conformance Statement

Doorbell Gateway

General Information

Product Identifier:	D1
Brand Name:	Starvedia
Product Version:	HW: 0 FW: 6.04:04.00:00.00:22.00
Z-Wave Certification #:	ZC10-19076689

Product Features

Supported Notification Types	CO Alarm CO2 Alarm Heat Alarm Smoke Alarm Water Alarm
Switch Load Capacity Current	1.5
Switch Load Capacity Volt-Ampere	20
Switch Load Capacity Watts	7.5
Communications Connections	Ethernet (Wireless/WiFi)
Communications Protocol	Manufacturer Proprietary Protocol
Firmware Updatable	Updatable by Consumer via Internet
Sensors	Humidity Luminance Power

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control, S2 Authenticated, S2 Unauthenticated

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Doorbell Gateway

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0009
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.03
Z-Wave Library Type:	Static Controller
Z-Wave Device Type / Role Type:	Central Controller / Central Static Controller

Association Group Information

Group # / Max Description

Nodes

1 / 1 Z-Wave Plus Lifeline, report Device Reset Locally when reset.

Supported Command Classes (15):

Application Status	Association Group Info
Association V2	CRC16 Encapsulation
Device Reset Locally	Inclusion Controller
Manufacturer Specific	Manufacturer Specific V2
Powerlevel	Security S0
Security S2	Supervision
Transport Service V2	Version V2
Z-Wave Plus Info V2	

Controlled Command Classes (19):

Association V2	Basic
Battery	CRC16 Encapsulation
Door Lock	Manufacturer Specific V2
Meter	Multi-Channel Association V3
Multi-Channel V4	Notification V4
Security S0	Security S2
Sensor Binary V2	Sensor Multilevel
Switch Binary	Switch Color
Switch Multilevel V2	Version V2
Wake Up V2	