

Z-Wave Protocol Implementation Conformance Statement

Smart On/Off Switch

General Information

Product Identifier:	MS10Z
Brand Name:	Minoston
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-19086728

Product Features

Z-Wave Scene Type	Scene
Switch Type	Push Button
Electric Load Type	Fluorescent Incandescent LED
Switch Load Capacity Current	15A
Switch Load Capacity Watts	960W
Color	White
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart On/Off Switch

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0xFF03
Z-Wave Product Type:	0xFF01
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.03
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 1 Z-Wave Plus Lifeline
2 / 5 basic set command

Supported Command Classes (16):

Association Group Info	Association V2
Basic V2	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Powerlevel
Security S2	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2