

Z-Wave Protocol Implementation Conformance Statement

Tunable White Smart Bulb

General Information

Product Identifier:	LZW41
Brand Name:	Illumin by Inovelli
Product Version:	HW: 255 FW: 2.24
Z-Wave Certification #:	ZC10-19086719

Product Features

Firmware Updatable	Updatable by Manufacturer
---------------------------	---------------------------

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0001
Z-Wave Product Type:	0x0006
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.51.09
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 1	1. When the state of the LED Bulb is changed: a) Set Configuration parameter 50 to 0: Nothing. b) Set Configuration parameter 50 to 1: Sending Switch Multilevel Report. 2. Device Reset Locally.
-------	---

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Tunable White Smart Bulb

Supported Command Classes (14):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Powerlevel
Security S0	Switch All
Switch Color	Switch Multilevel V2
Version V2	Z-Wave Plus Info V2