

Z-Wave Protocol Implementation Conformance Statement

Z-Wave Repeater

General Information

Product Identifier:	ZRP-120NA
Brand Name:	Remotec
Product Version:	HW: 1 FW: 0.10
Z-Wave Certification #:	ZC10-19086730

Product Features

Color	White
--------------	-------

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x8141
Z-Wave Product Type:	0x1000
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.71.01
Z-Wave Library Type:	Routing Slave
Z-Wave Device Type / Role Type:	Repeater / Always On Slave

Association Group Information

Group # / Max Nodes	Description
1 / 1	ZRP-120 supports 1 association group Association Group #1 Association Group #1 (max. 1 node) is default to associate with the primary controller (Gateway/Hub/Controller) for Z-Wave Repeater Status change report, refer to below for report details: a) Device Reset Locally Notification (Only report when the Z-Wave Repeater has been triggered the RESET TO DEFAULT)

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Repeater

Supported Command Classes (11):

Association Group Information V2

Device Reset Locally

Powerlevel

Security S2

Transport Service V2

Z-Wave Plus Info V2

Association V2

Manufacturer Specific V2

Security S0

Supervision

Version V2