

## Z-Wave Protocol Implementation Conformance Statement

### homee Z-Wave Cube Green

#### General Information

<b>Product Identifier:</b>	ESTMK-Z-Wave
<b>Brand Name:</b>	homee
<b>Product Version:</b>	HW: 2 FW: 6.01:02.81:01.00:01.00
<b>Z-Wave Certification #:</b>	ZC10-19096756

#### Product Features

<b>Gateway Has Preferred Partners</b>	No
<b>Sensors</b>	Air Temperature Carbon Dioxide Current Humidity Loudness Moisture Motion/No Motion (Binary) Power Rain Rate Voltage
<b>Supported Meter Type</b>	Electric Energy
<b>Supported Notification Types</b>	CO2 Alarm Emergency Alarm Power Management Siren Smoke Alarm
<b>Communications Protocol</b>	Manufacturer Proprietary Protocol
<b>Communications Connections</b>	USB (Universal Serial Bus)
<b>Firmware Updatable</b>	Updatable by Manufacturer

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## homee Z-Wave Cube Green

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control, S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x3900
<b>Z-Wave Product Type:</b>	0x0013
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.01
<b>Z-Wave Library Type:</b>	Bridge Controller
<b>Z-Wave Device Type / Role Type:</b>	Gateway / Central Static Controller

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 1                    homee supports the association group 1 (Lifeline). A maximum number of 1 node can be added to this association group. The only event sent to this group is the device reset locally notification.

**Supported Command Classes (20):**

Application Status	Association Group Information V3
Association V2	CRC16 Encapsulation
Device Reset Locally	Inclusion Controller
Mailbox	Manufacturer Specific V2
Multi-Command	Network Management Basic V2
Network Management Inclusion V3	Network Management Installation and Maintenance
Network Management Proxy V2	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
Version V2	Z-Wave Plus Info V2

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## homee Z-Wave Cube Green

### Controlled Command Classes (30):

Association V2

Battery

Configuration V4

Door Lock V3

Meter V3

Multi-Channel V4

Network Management Inclusion V3

Network Management Proxy V2

Notification V8

Security S0

Sensor Alarm

Switch Binary V2

Switch Multilevel V4

Thermostat Setpoint V3

Z/IP Portal

Basic

Central Scene V3

CRC16 Encapsulation

Manufacturer Specific V2

Multi-Channel Association V3

Network Management Basic V2

Network Management Installation and Maintenance

No Operation

Protection V2

Security S2

Sensor Binary V2

Switch Color V3

Thermostat Mode V3

Wake Up V2

Z/IP V3