

## Z-Wave Protocol Implementation Conformance Statement

### Radio Base Modul

#### General Information

<b>Product Identifier:</b>	MTBAS-100-WL
<b>Brand Name:</b>	myTEM SmartHome
<b>Product Version:</b>	HW: 1 FW: 6.04:02.81:01.00:01.00
<b>Z-Wave Certification #:</b>	ZC10-19106781

#### Product Features

<b>Communications Protocol</b>	Manufacturer Proprietary Protocol
<b>Gateway Has Preferred Partners</b>	No
<b>Supported Notification Types</b>	(No feature option values set for this feature)
<b>Sensors</b>	(No feature option values set for this feature)
<b>Communications Connections</b>	(No feature option values set for this feature)
<b>Supported Meter Type</b>	(No feature option values set for this feature)

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control, S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0x0101
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.81.03
<b>Z-Wave Library Type:</b>	Bridge Controller

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Radio Base Modul

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1                Z-Wave Plus Lifeline

**Supported Command Classes (18):**

Application Status	Association Group Information V3
Association V2	CRC16 Encapsulation
Device Reset Locally	Inclusion Controller
Manufacturer Specific V2	Multi-Command
Network Management Basic V2	Network Management Inclusion V3
Network Management Proxy V2	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2
Version V2	Z-Wave Plus Info V2

**Controlled Command Classes (28):**

Association V2	Basic V2
Battery	Central Scene V3
Configuration V4	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Meter V3
Multi-Channel Association V3	Multi-Channel V4
Multi-Command	Notification V8
Security S0	Security S2
Sensor Binary V2	Sensor Multilevel V11
Supervision	Switch Binary V2
Switch Color V3	Switch Multilevel V4
Thermostat Mode V3	Thermostat Setpoint V3
Transport Service V2	Version V2
Wake Up V2	Z-Wave Plus Info V2