

Z-Wave Protocol Implementation Conformance Statement

Z-WAVE PLUS ON / OFF LIGHT SWITCH

General Information

Product Identifier:	ZEN21 VER 3.0
Brand Name:	Zooz
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-19096759

Product Features

Color	White
Electric Load Type	Fluorescent Incandescent LED
Firmware Updatable	Updatable by Consumer by RF
Neutral Wire Required	Yes
Switch Load Capacity Current	15
Switch Load Capacity Watts	960
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-WAVE PLUS ON / OFF LIGHT SWITCH

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0xAA01
Z-Wave Product Type:	0xAA00
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.03
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 1	This device will send BASIC REPORT to Group 1 when operated manually.
2 / 5	This device will send BASIC SET to group 2 when operated manually.

Supported Command Classes (16):

Association Group Info	Association V2
Basic V2	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Powerlevel
Security S2	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2