

## Z-Wave Protocol Implementation Conformance Statement

# All-In-One Touchscreen Security

### General Information

<b>Product Identifier:</b>	PROA7PLUS
<b>Brand Name:</b>	Honeywell Home (Resideo)
<b>Product Version:</b>	HW: 1 FW: 6.06:02.81:02.00
<b>Z-Wave Certification #:</b>	ZC10-19116796

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control, S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	No

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0001
<b>Z-Wave Product Type:</b>	0x0001
<b>Z-Wave Hardware Platform:</b>	ZM5202
<b>Z-Wave Development Kit Version:</b>	6.81.05
<b>Z-Wave Library Type:</b>	Bridge Controller
<b>Z-Wave Device Type / Role Type:</b>	Central Controller / Central Static Controller

### Association Group Information

**Group # / Max Description**

#### Nodes

1 / 3 Controller - not typically used.

#### Supported Command Classes (18):

Application Status	Association Group Information V3
Association V2	CRC16 Encapsulation
Device Reset Locally	Inclusion Controller
Manufacturer Specific	Network Management Basic
Network Management Inclusion	Network Management Installation and Maintenance
Network Management Proxy	Powerlevel
Security S0	Security S2
Supervision	Transport Service V2

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## All-In-One Touchscreen Security

### Controlled Command Classes (15):

Association V2

CRC16 Encapsulation

Multi-Channel Association V3

Security S0

Sensor Multilevel V11

Switch Multilevel V4

Thermostat Mode V3

Wake Up V2

Basic

Door Lock V3

Multi-Channel V4

Security S2

Switch Binary V2

Thermostat Fan Mode V4

Thermostat Setpoint V3