

Z-Wave Protocol Implementation Conformance Statement

Recessed Door Sensor 7

General Information

Product Identifier:	ZW187-C
Brand Name:	Aeotec
Product Version:	HW: 187 FW: 1.02
Z-Wave Certification #:	ZC12-19110018

Product Features

Battery Quantity	1
Battery Type	CR2
Color	White
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x00BB
Z-Wave Product Type:	0x0002
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.11.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Recessed Door Sensor 7

2 / 5 Issue Basic Set when Magnet is away or near. (The Basic Set Value is determined by Configuration Parameter 3)

Supported Command Classes (20):

Application Status	Association Group Information V3
Association V2	Battery
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V3
Notification V8	Powerlevel
Security S0	Security S2
Sensor Binary V2	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2