

Z-Wave Protocol Implementation Conformance Statement

Outdoor Smart Plug - 1 channel

General Information

Product Identifier:	ZW96S
Brand Name:	EVA LOGIK
Product Version:	HW: 255 FW: 1.255
Z-Wave Certification #:	ZC10-19116793

Product Features

Firmware Updatable	Updatable by Consumer by RF
Outdoor Use	Yes
Color	Black
Electric Load Type	Fluorescent Incandescent Inductive (e.g. Motor) LED
Switch Load Capacity Current	15A

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0xC006
Z-Wave Product Type:	0xC000
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.71.01

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Outdoor Smart Plug - 1 channel

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 z-wave Lifeline

2 / 5 basic set command

Supported Command Classes (17):

- | | |
|--------------------------|------------------------------|
| Association Group Info | Association V2 |
| Basic V2 | Configuration |
| Device Reset Locally | Firmware Update Meta-Data V4 |
| Manufacturer Specific V2 | Multi-Channel Association V3 |
| Notification V8 | Powerlevel |
| Security S0 | Security S2 |
| Supervision | Switch Binary |
| Transport Service V2 | Version V2 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (1):

- Basic V2