

Z-Wave Protocol Implementation Conformance Statement

Smart Plug

General Information

Product Identifier:	HKZW-SO07
Brand Name:	Hank
Product Version:	HW: 1 FW: 1.03
Z-Wave Certification #:	ZC10-19126819

Product Features

Firmware Updatable	Updatable by Consumer by RF
Communications Protocol	Z-Wave Serial API
Switch Load Capacity Volt-Ampere	120V
Color	White
Switch Load Capacity Watts	1800W
Electric Load Type	Dimmable ELV (Magnetic) Dimmable Fluorescent Dimmable LED Dimmable MLV (Magnetic) ELV (Electronic) Fluorescent Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
Switch Type	Push Button Illuminated
Supported Meter Type	(No feature option values set for this feature)
Switch Load Capacity Current	15A

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Plug

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0016
Z-Wave Product Type:	0x0101
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	On/Off Power Switch / Always On Slave

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 Z-Wave Plus Lifeline

Supported Command Classes (18):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V3
Manufacturer Specific V2	Meter V3
Powerlevel	Scene Activation
Scene Actuator Conf	Security S0
Security S2	Supervision
Switch Binary	Transport Service V2
Version V2	Z-Wave Plus Info V2