

Z-Wave Protocol Implementation Conformance Statement

Plug-in Outdoor Switch

General Information

Product Identifier: 39346 / ZW4201
Brand Name: Honeywell
Product Version: HW: 255 FW: 5.21
Z-Wave Certification #: ZC10-19126817

Product Features

Color	Black
Firmware Updatable	Updatable by Consumer by RF
Outdoor Use	Yes
Switch Load Capacity Current	15
Switch Load Capacity Watts	1800
Switch Type	Push Button

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	No
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3032
Z-Wave Product Type:	0x4F50
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.51.10
Z-Wave Library Type:	Enhanced 232 Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Plug-in Outdoor Switch

Association Group Information

Group # / Max Description

Nodes

- 1 / 5 Supports Device Reset Locally and receives unsolicited status updates.
- 2 / 5 Association Group 2 supports Basic Set and is controlled by single pressing the button.
- 3 / 5 Association Group 3 supports Basic Set and is controlled by double pressing the button

Supported Command Classes (14):

Association Group Info	Association V2
Basic	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V2
Manufacturer Specific V2	Powerlevel
Scene Activation	Scene Actuator Conf
Switch All	Switch Binary
Version V2	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic