

Z-Wave Protocol Implementation Conformance Statement

Zerodim Z-Wave

General Information

Product Identifier:	1414141
Brand Name:	Q-light
Product Version:	HW: 255 FW: 4.03
Z-Wave Certification #:	ZC10-20036887

Product Features

Color	White
Firmware Updatable	Not Updatable
Neutral Wire Required	Yes
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x000D
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Zerodim Z-Wave

2 / 5 Mirror of endpoint 1, group 2.

3 / 5 Mirror of endpoint 1, group 3.

Supported Command Classes (20):

Association Group Info

Basic V2

Device Reset Locally

Manufacturer Specific V2

Multi-Channel V4

Powerlevel

Scene Actuator Conf

Security S2

Switch Multilevel V4

Version V3

Association V2

Configuration

Firmware Update Meta-Data V4

Multi-Channel Association V3

Notification V8

Scene Activation

Security S0

Supervision

Transport Service V2

Z-Wave Plus Info V2

Controlled Command Classes (2):

Basic V2

Switch Multilevel V4