

Z-Wave Protocol Implementation Conformance Statement

Double Switch

General Information

Product Identifier:	ZEN30
Brand Name:	Zooz
Product Version:	HW: 2 FW: 1.00
Z-Wave Certification #:	ZC10-20026859

Product Features

Color	White
Electric Load Type	Dimmable ELV (Magnetic) Dimmable LED Dimmable MLV (Magnetic) Incandescent Inductive (e.g. Motor) LED MLV (Magnetic)
Firmware Updatable	Updatable by Consumer by RF
Loads Controlled	2
Neutral Wire Required	Yes
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Double Switch

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0xa008
Z-Wave Product Type:	0xa000
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.82.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max	Description
----------------------	--------------------

Nodes

1 / 1	The dimmer and relay will send basic_set reports to the hub when their status changes.
2 / 5	The dimmer supports Group 2 with up to 5 devices and will send BASIC_SET report to other devices in Group 2 to communicate status changes.
3 / 5	The relay supports Group 3 with up to 5 devices and will send BASIC_SET report to other devices in Group 3 if its status changes.

Supported Command Classes (18):

Association Group Info	Association V2
Basic V2	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Multi-Channel V4
Powerlevel	Security S2
Supervision	Switch Binary
Switch Multilevel V4	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2
