

Z-Wave Protocol Implementation Conformance Statement

ECO-DIM.07 Z-Wave LED dimmer

General Information

Product Identifier:	ECO-DIM.07 Z-Wave
Brand Name:	EcoDim BV
Product Version:	HW: 1 FW: 1.17
Z-Wave Certification #:	ZC10-20036885

Product Features

Communications Connections	(No feature option values set for this feature)
Switch Load Capacity Current	200W
Firmware Updatable	Updatable by Consumer by RF
Switch Type	Rotary Knob

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0001
Z-Wave Product Type:	0x0202
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.81.03
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

ECO-DIM.07 Z-Wave LED dimmer

Supported Command Classes (15):

Association Group Info
Basic
Device Reset Locally
Manufacturer Specific V2
Security S0
Supervision
Transport Service V2
Z-Wave Plus Info V2

Association V2
Configuration
Firmware Update Meta-Data V4
Powerlevel
Security S2
Switch Multilevel V2
Version V2