

Z-Wave Protocol Implementation Conformance Statement

DIN Rail Power Switch Meter

General Information

Product Identifier:	PSM-DIN2-ZW
Brand Name:	Climax Technology
Product Version:	HW: 255 FW: 4.01
Z-Wave Certification #:	ZC10-20036894

Product Features

Firmware Updatable	Updatable by Consumer by RF
Switch Type	Push Button

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0003
Z-Wave Product Type:	0x0004
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Sub Energy Meter / Always On Slave

Association Group Information

Group # / Max Nodes	Description
1 / 5	The Switch can be set to send reports to associated Z-Wave devices. It supports one association group with five node support for Grouping 1 (Lifeline). For grouping 1, the Switch will report its latest status to Z-Wave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

DIN Rail Power Switch Meter

Supported Command Classes (16):

Association Group Info	Association V2
Basic	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Meter V2
Multi-Channel Association V3	Powerlevel
Security S2	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2