

## Z-Wave Protocol Implementation Conformance Statement

### Fan Speed Controller

#### General Information

<b>Product Identifier:</b>	ZW4SF
<b>Brand Name:</b>	Leviton
<b>Product Version:</b>	HW: 1 FW: 1.07
<b>Z-Wave Certification #:</b>	ZC12-20040040

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Switch Load Capacity Current</b>	1.5A
<b>Neutral Wire Required</b>	Yes
<b>Z-Wave Scene Type</b>	Scene

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x0002
<b>Z-Wave Product Type:</b>	0x0038
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.12.2
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Multilevel Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Fan Speed Controller

### Supported Command Classes (19):

Association Group Information V3

Basic V2

Device Reset Locally

Indicator V3

Multi-Channel Association V3

Scene Activation

Security S0

Supervision

Transport Service V2

Z-Wave Plus Info V2

Association V2

Configuration V4

Firmware Update Meta-Data V5

Manufacturer Specific V2

Powerlevel

Scene Actuator Conf

Security S2

Switch Multilevel V4

Version V3