



Z-Wave Protocol Implementation Conformance Statement

Radio Switch Dimmer

General Information

Product Identifier:	MTSWD-100-WL
Brand Name:	myTEM SmartHome
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-20066920

Product Features

Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Watts	250
Electric Load Type	Dimmable LED
Switch Load Capacity Current	1
Switch Load Capacity Volt-Ampere	250

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0009
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.81.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Radio Switch Dimmer

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 Lifeline group. Reports resetting network and configuration parameter. Reports actual power and cummulated energy of output 1. Reports the device had a start-up (Power Management / Power has been applied) and periodically to be alive (System / Heartbeat)

Supported Command Classes (19):

Application Status	Association Group Info
Association V2	Basic
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Meter V4	Multi-Channel Association V3
Multi-Channel V4	Notification V8
Powerlevel	Security S2
Supervision	Switch Multilevel V4
Transport Service V2	Version V3
Z-Wave Plus Info V2	