

Z-Wave Protocol Implementation Conformance Statement

Ring Keypad v2

General Information

Product Identifier:	Keypad v2
Brand Name:	Ring
Product Version:	HW: 1 FW: 1.08
Z-Wave Certification #:	ZC12-20050056

Product Features

Color	White
--------------	-------

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x0301
Z-Wave Product Type:	0x0101
Z-Wave Hardware Platform:	EFR32Z
Z-Wave Development Kit Version:	7.12.4
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Entry Control Keypad Device / Listening Sleeping Slave

Association Group Information

Group # / Max Nodes	Description
1 / 5	This is the Lifeline group with the following command class support - 1. Notification Report a. See notification CC section for notifications that are sent 2. Entry Control Notification 3. Battery Report 4. Device Reset Locally Notification

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Ring Keypad v2

Supported Command Classes (18):

Association Group Information V3

Battery

Device Reset Locally

Firmware Update Meta-Data V5

Manufacturer Specific V2

Notification V8

Security S0

Supervision

Version V3

Association V2

Configuration V4

Entry Control

Indicator V3

Multi-Channel Association V3

Powerlevel

Security S2

Transport Service V2

Z-Wave Plus Info V2