

Z-Wave Protocol Implementation Conformance Statement

Universal module with 3 In 3 Out

General Information

Product Identifier:	SA301-1
Brand Name:	Everspring
Product Version:	HW: 1 FW: 1.00:00.04
Z-Wave Certification #:	ZC10-20056912

Product Features

Firmware Updatable	Updatable by Consumer by RF
Battery Type	1.5V AAA
Battery Quantity	4
Color	White

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0007
Z-Wave Product Type:	0x0003
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.81.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Always On Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Universal module with 3 In 3 Out

2 / 5 Mirror of endpoint 1
3 / 5 Mirror of endpoint 2
4 / 5 Mirror of endpoint 3

Supported Command Classes (19):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Firmware Update Meta-Data V4
Manufacturer Specific V2	Multi-Channel Association V3
Multi-Channel V4	Notification V8
Powerlevel	Security S0
Security S2	Sensor Multilevel V5
Supervision	Switch Binary
Transport Service V2	Version V3
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic