



Z-Wave Protocol Implementation Conformance Statement

WALLI CONTROLLER

General Information

Product Identifier:	FGWCEU-201
Brand Name:	Fibar Group S.A.
Product Version:	HW: 1 FW: 7.00
Z-Wave Certification #:	ZC12-20060078

Product Features

Battery Type	ER14250
Color	White
Firmware Updatable	Updatable by Consumer by RF
Z-Wave Scene Type	Central Scene
Battery Quantity	1

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Don't know
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x1000
Z-Wave Product Type:	0x2301
Z-Wave Hardware Platform:	ZGM130
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Central Scene Device / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

WALLI CONTROLLER

Association Group Information

Group # / Max Description

Nodes

1 / 1	"Lifeline" reports the device status and allows for assigning single device only (main controller by default).
2 / 5	"On/Off (1)" is used to turn the associated devices on/off.
3 / 5	"Dimmer (1)" is used to change level of associated devices.
4 / 5	"On/Off (2)" is used to turn the associated devices on/off.
5 / 5	"Dimmer (2)" is used to change level of associated devices.
6 / 5	"Multidevice" is used to control different type of devices.
7 / 5	"Slats" is used to move slats of venetian blinds.

Supported Command Classes (21):

Application Status	Association Group Information V3
Association V2	Battery
Central Scene V3	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V5
Indicator V3	Manufacturer Specific V2
Multi-Channel Association V3	Powerlevel
Protection	Security S0
Security S2	Sensor Multilevel V11
Supervision	Transport Service V2
Version V3	Wake Up V2
Z-Wave Plus Info V2	