

Z-Wave Protocol Implementation Conformance Statement

Universal module with 3 In 3 Out

General Information

Product Identifier:	SA301-1
Brand Name:	Everspring
Product Version:	HW: 1 FW: 1.01:00.01
Z-Wave Certification #:	ZC10-20056913

Product Features

Battery Quantity	4
Battery Type	AAA 1.5V
Color	White
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x0001
Z-Wave Product Type:	0x0016
Z-Wave Hardware Platform:	SD3502
Z-Wave Development Kit Version:	6.81.06
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Always On Slave

Association Group Information

Group # / Max	Description
---------------	-------------

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Universal module with 3 In 3 Out

2 / 5 Mirror of endpoint 1
3 / 5 Mirror of endpoint 2
4 / 5 Mirror of endpoint 3

Supported Command Classes (20):

Association Group Info	Association V2
Basic	Battery
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Multi-Channel V4
Notification V8	Powerlevel
Security S0	Security S2
Sensor Multilevel V5	Supervision
Switch Binary	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic