

Z-Wave Protocol Implementation Conformance Statement

Universal module with 3 In 3 Out

General Information

| | |
|--------------------------------|----------------------|
| Product Identifier: | SA301-1 |
| Brand Name: | Everspring |
| Product Version: | HW: 1 FW: 1.01:00.01 |
| Z-Wave Certification #: | ZC10-20056913 |

Product Features

| | |
|---------------------------|-----------------------------|
| Battery Quantity | 4 |
| Battery Type | AAA 1.5V |
| Color | White |
| Firmware Updatable | Updatable by Consumer by RF |

Z-Wave Product Information

| | |
|--------------------------------------|---|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | Yes: S2 Authenticated, S2 Unauthenticated |
| SmartStart Compatible? | Yes |

Z-Wave Technical Information

| | |
|--|---------------------------------------|
| Z-Wave Frequency: | CEPT (Europe) |
| Z-Wave Product ID: | 0x0001 |
| Z-Wave Product Type: | 0x0016 |
| Z-Wave Hardware Platform: | SD3502 |
| Z-Wave Development Kit Version: | 6.81.06 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Notification Sensor / Always On Slave |

Association Group Information

| Group # / Max | Description |
|---------------|-------------|
|---------------|-------------|

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Universal module with 3 In 3 Out

2 / 5 Mirror of endpoint 1
3 / 5 Mirror of endpoint 2
4 / 5 Mirror of endpoint 3

Supported Command Classes (20):

| | |
|------------------------------|--------------------------|
| Association Group Info | Association V2 |
| Basic | Battery |
| Configuration V4 | Device Reset Locally |
| Firmware Update Meta-Data V4 | Manufacturer Specific V2 |
| Multi-Channel Association V3 | Multi-Channel V4 |
| Notification V8 | Powerlevel |
| Security S0 | Security S2 |
| Sensor Multilevel V5 | Supervision |
| Switch Binary | Transport Service V2 |
| Version V3 | Z-Wave Plus Info V2 |

Controlled Command Classes (1):

Basic