

## Z-Wave Protocol Implementation Conformance Statement

### DIMMER 2 400W

#### General Information

<b>Product Identifier:</b>	DIMMER 2 400W
<b>Brand Name:</b>	Namron
<b>Product Version:</b>	HW: 1 FW: 1.06
<b>Z-Wave Certification #:</b>	ZC10-20076932

#### Product Features

<b>Firmware Updatable</b>	Updatable by Consumer by RF
<b>Supported Meter Type</b>	Electric Energy
<b>Supported Notification Types</b>	Power Management System

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	CEPT (Europe)
<b>Z-Wave Product ID:</b>	0xD00C
<b>Z-Wave Product Type:</b>	0x0200
<b>Z-Wave Hardware Platform:</b>	ZM5101
<b>Z-Wave Development Kit Version:</b>	6.71.03
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Light Dimmer Switch / Always On Slave

#### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## DIMMER 2 400W

### Supported Command Classes (19):

Association Group Information V3

Basic V2

Device Reset Locally

Manufacturer Specific V2

Notification V8

Scene Activation

Security S0

Supervision

Transport Service V2

Z-Wave Plus Info V2

Association V2

Configuration

Firmware Update Meta-Data V4

Meter V3

Powerlevel

Scene Actuator Conf

Security S2

Switch Multilevel V4

Version V2