

Z-Wave Protocol Implementation Conformance Statement

Z-Wave Dimmer

General Information

Product Identifier:	SQR22101**Z
Brand Name:	Square D
Product Version:	HW: 1 FW: 1.13
Z-Wave Certification #:	ZC10-20076943

Product Features

Switch Load Capacity Volt-Ampere

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x1201
Z-Wave Product Type:	0x0111
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.82.01
Z-Wave Library Type:	Routing Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 5	Lifeline: Send device reset locally notification MultiLevelReport:Dimming percentage report MeterReport:Power metering report

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Z-Wave Dimmer

Supported Command Classes (14):

Association Group Info	Association V2
Basic	Configuration
Device Reset Locally	Manufacturer Specific V2
Meter V3	Powerlevel
Security S2	Supervision
Switch Multilevel V2	Transport Service V2
Version V2	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic