

## Z-Wave Protocol Implementation Conformance Statement

### Smart Flood/Freeze Sensor

#### General Information

<b>Product Identifier:</b>	52247/ZW6309
<b>Brand Name:</b>	Jasco
<b>Product Version:</b>	HW: 1 FW: 7.03
<b>Z-Wave Certification #:</b>	ZC12-20100126

#### Product Features

<b>Battery Quantity</b>	1
<b>Battery Type</b>	CR123
<b>Firmware Updatable</b>	Updatable by Consumer by RF

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

#### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x3430
<b>Z-Wave Product Type:</b>	0x4953
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.5
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Notification Sensor / Always On Slave

#### Association Group Information

Group # / Max Nodes	Description
---------------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Smart Flood/Freeze Sensor

### Supported Command Classes (17):

Association Group Information V3

Battery

Device Reset Locally

Indicator V3

Multi-Channel Association V3

Powerlevel

Supervision

Version V2

Z-Wave Plus Info V2

Association V2

Configuration V4

Firmware Update Meta-Data V5

Manufacturer Specific

Notification V8

Security S2

Transport Service V2

Wake Up V2