

Z-Wave Protocol Implementation Conformance Statement

Slim Smart Door/Window Sensor

General Information

Product Identifier:	52249/ZW6308
Brand Name:	Jasco
Product Version:	HW: 1 FW: 7.07
Z-Wave Certification #:	ZC12-20080113

Product Features

Battery Type	CR2450
Firmware Updatable	Updatable by Consumer by RF
Battery Quantity	1

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3336
Z-Wave Product Type:	0x4953
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.13.5
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Notification Sensor / Reporting Sleeping Slave

Association Group Information

Group # / Max	Description
Nodes	

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Slim Smart Door/Window Sensor

Supported Command Classes (18):

Application Status	Association Group Information V3
Association V2	Battery
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V3
Notification V8	Powerlevel
Security S2	Supervision
Transport Service V2	Version V3
Wake Up V2	Z-Wave Plus Info V2