

Z-Wave Protocol Implementation Conformance Statement

Portable Remote, Simple Controller, 4 Button

General Information

| | |
|--------------------------------|----------------|
| Product Identifier: | 53831/ZW5314 |
| Brand Name: | Jasco |
| Product Version: | HW: 1 FW: 7.03 |
| Z-Wave Certification #: | ZC12-20090120 |

Product Features

| | |
|---------------------------|-----------------------------|
| Battery Type | CR2032 |
| Firmware Updatable | Updatable by Consumer by RF |
| Z-Wave Scene Type | Central Scene |
| Battery Quantity | 2 |

Z-Wave Product Information

| | |
|--------------------------------------|---|
| Supports Z-Wave Beaming Technology? | No |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | Yes |
| Supports Security S2? | Yes: S2 Authenticated, S2 Unauthenticated |
| SmartStart Compatible? | Yes |

Z-Wave Technical Information

| | |
|--|---|
| Z-Wave Frequency: | U.S. / Canada / Mexico |
| Z-Wave Product ID: | 0x3138 |
| Z-Wave Product Type: | 0x4843 |
| Z-Wave Hardware Platform: | ZGM130 |
| Z-Wave Development Kit Version: | 7.13.6 |
| Z-Wave Library Type: | Portable Controller |
| Z-Wave Device Type / Role Type: | Central Scene Device / Reporting Sleeping Slave |

Association Group Information

| Group # / Max | Description |
|---------------|-------------|
|---------------|-------------|

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Portable Remote, Simple Controller, 4 Button

2 / 5 Association Group 2 supports Basic Set and is controlled by pressing the UP or Down button

3 / 5 Association Group 3 supports Basic Set and is controlled by double pressing the UP or Down button

Supported Command Classes (19):

Application Status

Association V2

Central Scene V3

Device Reset Locally

Indicator V3

Multi-Channel Association V3

Security S0

Supervision

Version V3

Z-Wave Plus Info V2

Association Group Information V3

Battery

Configuration V4

Firmware Update Meta-Data V5

Manufacturer Specific V2

Powerlevel

Security S2

Transport Service V2

Wake Up V2