

Z-Wave Protocol Implementation Conformance Statement

In-Wall 3-Speed Fan Control

General Information

Product Identifier:	55259/ZW4002
Brand Name:	Jasco
Product Version:	HW: 255 FW: 5.50
Z-Wave Certification #:	ZC10-20086967

Product Features

Firmware Updatable	Updatable by Consumer by RF
Neutral Wire Required	Yes
Switch Load Capacity Current	2.5
Switch Type	Decorator Paddle Push
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3338
Z-Wave Product Type:	0x4944
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.82.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Fan Switch / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

In-Wall 3-Speed Fan Control

Association Group Information

Group # / Max Description

Nodes

- 1 / 5 Z-Wave Plus Lifeline
- 2 / 5 Supports Basic Set and is controlled with the local load
- 3 / 5 Supports Basic Set and is controlled by double pressing the On or Off button

Supported Command Classes (16):

- | | |
|--------------------------|------------------------------|
| Application Status | Association Group Info |
| Association V2 | Basic V2 |
| Central Scene V3 | Configuration V4 |
| Device Reset Locally | Firmware Update Meta-Data V4 |
| Manufacturer Specific V2 | Powerlevel |
| Security S2 | Supervision |
| Switch Multilevel V4 | Transport Service V2 |
| Version V3 | Z-Wave Plus Info V2 |