

Z-Wave Protocol Implementation Conformance Statement

S2 In-wall Smart Dimmer switch

General Information

Product Identifier:	MS11ZS
Brand Name:	Minoston
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-20096981

Product Features

Electric Load Type	Dimmable LED Incandescent LED
Firmware Updatable	Updatable by Consumer by RF
Switch Load Capacity Watts	500W
Switch Type	Push Button
Color	White

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Unauthenticated
SmartStart Compatible?	No

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0xEE02
Z-Wave Product Type:	0xEE00
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.81.03
Z-Wave Library Type:	Enhanced 232 Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

S2 In-wall Smart Dimmer switch

Association Group Information

Group # / Max **Description**

Nodes

1 / 3 Z-Wave Lifeline

2 / 5 basic set command

Supported Command Classes (16):

Association Group Info	Association V2
Basic V2	Central Scene V3
Configuration	Device Reset Locally
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Powerlevel
Security S2	Supervision
Switch Multilevel V4	Transport Service V2
Version V3	Z-Wave Plus Info V2

Controlled Command Classes (1):

Basic V2