

Z-Wave Protocol Implementation Conformance Statement

Chime+Siren

General Information

Product Identifier:	ISZW7-ECO
Brand Name:	Ecolink
Product Version:	HW: 1 FW: 2.00:01.10
Z-Wave Certification #:	ZC12-20100128

Product Features

Color	White
--------------	-------

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3975
Z-Wave Product Type:	0x0007
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.13.6
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Sound Switch DT / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 1	This sensor has one Association group (Lifeline) with only one node for that group. Group one is a lifeline group who will receive unsolicited messages relating to AC and Battery power notifications, and Device Reset Locally notifications.

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Chime+Siren

Supported Command Classes (18):

Association Group Information V3

Basic V2

Configuration V4

Firmware Update Meta-Data V5

Manufacturer Specific V2

Notification V8

Security S2

Supervision

Version V3

Association V2

COMMAND_CLASS_BATTERY_V2

Device Reset Locally

Indicator V3

Multi-Channel Association V3

Powerlevel

Sound Switch

Transport Service V2

Z-Wave Plus Info V2