

Z-Wave Protocol Implementation Conformance Statement

0-10V In-Wall Smart Dimmer (ICP) (120/277)

General Information

Product Identifier:	43107 / ZW3015
Brand Name:	Jasco
Product Version:	HW: 255 FW: 5.52
Z-Wave Certification #:	ZC10-20096973

Product Features

Firmware Updatable	Updatable by Consumer by RF
Neutral Wire Required	Yes
Switch Load Capacity Volt-Ampere	960
Switch Type	Toggle
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3332
Z-Wave Product Type:	0x4944
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.82.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

0-10V In-Wall Smart Dimmer (ICP) (120/277)

Association Group Information

Group # / Max Description

Nodes

1 / 5 Association Group 1 supports Lifeline, Multi-level Switch report

2 / 5 Association Group 2 supports Basic Set and is controlled with the local load

3 / 5 Association Group 3 supports Basic Set and is controlled by double pressing the ON or OFF button

Supported Command Classes (15):

Application Status	Association Group Info
Association V2	Basic V2
Central Scene V3	Configuration V4
Device Reset Locally	Manufacturer Specific V2
Powerlevel	Security S2
Supervision	Switch Multilevel V4
Transport Service V2	Version V3
Z-Wave Plus Info V2	

Controlled Command Classes (1):

Basic V2