

Z-Wave Protocol Implementation Conformance Statement

0-10V In-Wall Smart Dimmer (ICP) (120/277)

General Information

Product Identifier:	43107 / ZW3015
Brand Name:	Jasco
Product Version:	HW: 255 FW: 5.53
Z-Wave Certification #:	ZC10-20116995

Product Features

Firmware Updatable	Updatable by Consumer by RF
Neutral Wire Required	Yes
Switch Load Capacity Volt-Ampere	960
Switch Type	Left/Right Rocker with Indicator
Z-Wave Scene Type	Scene & Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3332
Z-Wave Product Type:	0x4944
Z-Wave Hardware Platform:	ZM5202
Z-Wave Development Kit Version:	6.82.00
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Light Dimmer Switch / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

0-10V In-Wall Smart Dimmer (ICP) (120/277)

Association Group Information

Group # / Max **Description**

Nodes

- 1 / 5 Association Group 1 supports Lifeline, Multi-level Switch report
- 2 / 5 Association Group 2 supports Basic Set and is controlled with the local load
- 3 / 5 Association Group 3 supports Basic Set and is controlled by double pressing the ON or OFF button

Supported Command Classes (15):

- | | |
|----------------------|--------------------------|
| Application Status | Association Group Info |
| Association V2 | Basic V2 |
| Central Scene V3 | Configuration V4 |
| Device Reset Locally | Manufacturer Specific V2 |
| Powerlevel | Security S2 |
| Supervision | Switch Multilevel V4 |
| Transport Service V2 | Version V3 |
| Z-Wave Plus Info V2 | |

Controlled Command Classes (1):

- Basic V2