

Z-Wave Protocol Implementation Conformance Statement

Radio Switch Shutter Plus

General Information

Product Identifier:	MTSWIS-101-WL
Brand Name:	myTEM SmartHome
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC10-21027009

Product Features

Electric Load Type	Inductive (e.g. Motor)
Switch Load Capacity Current	2x 6A, 250VAC or 30VDC
Firmware Updatable	Updatable by Consumer by RF
Supported Notification Types	Power Management System
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	CEPT (Europe)
Z-Wave Product ID:	0x000C
Z-Wave Product Type:	0x0001
Z-Wave Hardware Platform:	ZM5101
Z-Wave Development Kit Version:	6.82.01
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Window Covering - Endpoint Aware / Always On Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Radio Switch Shutter Plus

Association Group Information

Group # / Max **Description**

Nodes

1 / 5 Z-Wave Plus Lifeline System / Heartbeat; sent periodically (see Configuration Parameter Heartbeat) Power Mangement / Power has been applied; sent after Powerup and Reset

Supported Command Classes (18):

Application Status	Association Group Information V3
Association V2	Basic
Central Scene V3	Configuration V4
Firmware Update Meta-Data V4	Manufacturer Specific V2
Multi-Channel Association V3	Multi-Channel V4
Notification V8	Powerlevel
Security S2	Supervision
Switch Multilevel V4	Transport Service V2
Version V3	Z-Wave Plus Info V2