

## Z-Wave Protocol Implementation Conformance Statement

# Yale Assure Lock™ Z-Wave Enabled Keypad Deadbolt

### General Information

<b>Product Identifier:</b>	YRD216-ZW3
<b>Brand Name:</b>	Yale
<b>Product Version:</b>	HW: 2 FW: 2.13:43.19
<b>Z-Wave Certification #:</b>	ZC12-21020188

### Product Features

<b>Battery Type</b>	AA
<b>Color</b>	Antique Brass
<b>Communications Connections</b>	None
<b>Communications Protocol</b>	Z-Wave Serial API
<b>Controller Supports Multiple Z-Wave Interfaces</b>	No
<b>Door Lock Type</b>	Deadbolt
<b>Battery Quantity</b>	4
<b>Firmware Updatable</b>	Updatable by Consumer by RF

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## Yale Assure Lock™ Z-Wave Enabled Keypad Deadbolt

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x46D1
<b>Z-Wave Product Type:</b>	0x8004
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.12.2
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Lock / Listening Sleeping Slave

### Association Group Information

**Group # / Max**    **Description**

**Nodes**

1 / 3                    the description is lifeline.

**Supported Command Classes (26):**

Application Status	Association Group Information V3
Association V2	Basic V2
Battery	Clock
Configuration V4	Device Reset Locally
Door Lock Logging	Door Lock V4
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V3
Notification V8	Powerlevel
Schedule Entry Lock V3	Security S0
Security S2	Supervision
Time Parameters	Time V2
Transport Service V2	User Code V2
Version V3	Z-Wave Plus Info V2