

## Z-Wave Protocol Implementation Conformance Statement

### ON/OFF SWITCH 700

#### General Information

Product Identifier:	ZEN71
Brand Name:	Zooz
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC12-21020181

#### Product Features

Neutral Wire Required	Yes
Switch Load Capacity Current	15
Switch Load Capacity Watts	960
Z-Wave Scene Type	Central Scene
Color	White
Electric Load Type	Incandescent LED
Firmware Updatable	Updatable by Consumer by RF

#### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## ON/OFF SWITCH 700

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0xA001
<b>Z-Wave Product Type:</b>	0x7000
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.6
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Binary Switch / Always On Slave

### Association Group Information

**Group # / Max    Description**

**Nodes**

1 / 1	Lifeline communication between the switch and the hub.
2 / 5	Basic set communication for nodes in Group 2.

**Supported Command Classes (17):**

Association Group Information V3	Association V3
Basic V2	Central Scene V3
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific	Multi-Channel Association V3
Powerlevel	Security S2
Supervision	Switch Binary V2
Transport Service V2	Version V3
Z-Wave Plus Info V2	