



Z-Wave Protocol Implementation Conformance Statement

REMOTE SWITCH

General Information

Product Identifier:	ZEN34
Brand Name:	Zooz
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC12-21030192

Product Features

Firmware Updatable	Updatable by Consumer by RF
Battery Type	CR2032
Battery Quantity	2
Z-Wave Scene Type	Central Scene
Color	White

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0xF001
Z-Wave Product Type:	0x7000
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.13.6
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Central Scene Device / Reporting Sleeping Slave

(Continued)

REMOTE SWITCH

Association Group Information

Group # / Max Description

Nodes

1 / 1	Lifeline Communication to the hub.
2 / 5	Basic set to Group 2.
3 / 5	Switch multilevel to Group 3.

Supported Command Classes (17):

Association Group Information V3	Association V3
Battery	Central Scene V3
Configuration V4	Device Reset Locally
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V4
Powerlevel	Security S2
Supervision	Transport Service V2
Version V3	Wake Up V2
Z-Wave Plus Info V2	