

Z-Wave Protocol Implementation Conformance Statement

REMOTE SWITCH

General Information

Product Identifier:	ZEN34
Brand Name:	Zooz
Product Version:	HW: 1 FW: 1.00
Z-Wave Certification #:	ZC12-21030192

Product Features

Battery Quantity	2
Battery Type	CR2032
Color	White
Firmware Updatable	Updatable by Consumer by RF
Z-Wave Scene Type	Central Scene

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	No
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0xF001
Z-Wave Product Type:	0x7000
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.13.6
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Central Scene Device / Reporting Sleeping Slave

Z-Wave Protocol Implementation Conformance Statement

(Continued)

REMOTE SWITCH

Association Group Information

Group # / Max Description

Nodes

- 1 / 1 Lifeline Communication to the hub.
- 2 / 5 Basic set to Group 2.
- 3 / 5 Switch multilevel to Group 3.

Supported Command Classes (17):

- Association Group Information V3
- Battery
- Configuration V4
- Firmware Update Meta-Data V5
- Manufacturer Specific V2
- Powerlevel
- Supervision
- Version V3
- Z-Wave Plus Info V2
- Association V3
- Central Scene V3
- Device Reset Locally
- Indicator V3
- Multi-Channel Association V4
- Security S2
- Transport Service V2
- Wake Up V2