

Z-Wave Protocol Implementation Conformance Statement

Smart Plug In Switch

General Information

| | |
|--------------------------------|------------------|
| Product Identifier: | IQ Outlet |
| Brand Name: | Johnson Controls |
| Product Version: | HW: 1 FW: 7.08 |
| Z-Wave Certification #: | ZC12-21030207 |

Product Features

| | |
|-------------------------------------|--|
| Color | White |
| Switch Load Capacity Current | 15A |
| Switch Load Capacity Watts | 900W incandescent, 200W CFL/LED |
| Electric Load Type | Fluorescent Incandescent Inductive (e.g. Motor) LED |
| Firmware Updatable | Updatable by Consumer by RF |
| Outdoor Use | No |

Z-Wave Product Information

| | |
|--------------------------------------|---|
| Supports Z-Wave Beaming Technology? | Yes |
| Supports Z-Wave Network Security? | Yes |
| Supports Z-Wave AES-128 Security S0? | No |
| Supports Security S2? | Yes: S2 Authenticated, S2 Unauthenticated |
| SmartStart Compatible? | Yes |

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Plug In Switch

Z-Wave Technical Information

| | |
|--|---------------------------------|
| Z-Wave Frequency: | U.S. / Canada / Mexico |
| Z-Wave Product ID: | 0x3033 |
| Z-Wave Product Type: | 0x4744 |
| Z-Wave Hardware Platform: | ZGM130 |
| Z-Wave Development Kit Version: | 7.13.7 |
| Z-Wave Library Type: | Enhanced 232 Slave |
| Z-Wave Device Type / Role Type: | Binary Switch / Always On Slave |

Association Group Information

Group # / Max Description

Nodes

| | |
|-------|---|
| 1 / 5 | IQ Outlet supports Group 1 for lifeline communication |
| 2 / 5 | The devices in Association Group 2 can be controlled (on/off) by single pressing the button using Basic Set |

Supported Command Classes (20):

| | |
|------------------------------|----------------------------------|
| Application Status | Association Group Information V3 |
| Association V2 | Basic V2 |
| COMMAND_CLASS_METER_V6 | Configuration V4 |
| Device Reset Locally | Firmware Update Meta-Data V5 |
| Indicator V3 | Manufacturer Specific V2 |
| Multi-Channel Association V3 | Powerlevel |
| Scene Activation | Scene Actuator Conf |
| Security S2 | Supervision |
| Switch Binary V2 | Transport Service V2 |
| Version V3 | Z-Wave Plus Info V2 |