

Z-Wave Protocol Implementation Conformance Statement

Smart Plug In Switch

General Information

Product Identifier:	IQ Outlet
Brand Name:	Johnson Controls
Product Version:	HW: 1 FW: 7.08
Z-Wave Certification #:	ZC12-21030207

Product Features

Color	White
Switch Load Capacity Current	15A
Switch Load Capacity Watts	900W incandescent, 200W CFL/LED
Electric Load Type	Fluorescent Incandescent Inductive (e.g. Motor) LED
Firmware Updatable	Updatable by Consumer by RF
Outdoor Use	No

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	No
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Protocol Implementation Conformance Statement

(Continued)

Smart Plug In Switch

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x3033
Z-Wave Product Type:	0x4744
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.13.7
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Binary Switch / Always On Slave

Association Group Information

Group # / Max Description

Nodes

1 / 5	IQ Outlet supports Group 1 for lifeline communication
2 / 5	The devices in Association Group 2 can be controlled (on/off) by single pressing the button using Basic Set

Supported Command Classes (20):

Application Status	Association Group Information V3
Association V2	Basic V2
COMMAND_CLASS_METER_V6	Configuration V4
Device Reset Locally	Firmware Update Meta-Data V5
Indicator V3	Manufacturer Specific V2
Multi-Channel Association V3	Powerlevel
Scene Activation	Scene Actuator Conf
Security S2	Supervision
Switch Binary V2	Transport Service V2
Version V3	Z-Wave Plus Info V2