

## Z-Wave Protocol Implementation Conformance Statement

# 10 Button Z-Wave Plus v2 Deadbolt

### General Information

<b>Product Identifier:</b>	Home Connect 620
<b>Brand Name:</b>	Kwikset
<b>Product Version:</b>	HW: 1 FW: 7.16:69.31
<b>Z-Wave Certification #:</b>	ZC12-21060240

### Product Features

<b>Battery Quantity</b>	4
<b>Battery Type</b>	R6 (disposable alkaline AA)
<b>Door Lock Type</b>	Deadbolt
<b>Firmware Updatable</b>	Not Updatable

### Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Access Control
SmartStart Compatible?	Yes

### Z-Wave Technical Information

<b>Z-Wave Frequency:</b>	U.S. / Canada / Mexico
<b>Z-Wave Product ID:</b>	0x03A8
<b>Z-Wave Product Type:</b>	0x0811
<b>Z-Wave Hardware Platform:</b>	ZGM130
<b>Z-Wave Development Kit Version:</b>	7.13.6
<b>Z-Wave Library Type:</b>	Enhanced 232 Slave
<b>Z-Wave Device Type / Role Type:</b>	Lock / Listening Sleeping Slave

### Association Group Information

Group # / Max	Description
---------------	-------------

# Z-Wave Protocol Implementation Conformance Statement

(Continued)

## 10 Button Z-Wave Plus v2 Deadbolt

### Supported Command Classes (24):

Anti-Theft V2	Association Group Information V3
Association V2	Basic V2
Battery	Configuration V4
Device Reset Locally	Door Lock Logging
Door Lock V4	Firmware Update Meta-Data V5
Indicator V3	Manufacturer Specific V2
Multi-Channel Association V3	Notification V8
Powerlevel	Schedule Entry Lock V3
Security S0	Security S2
Supervision	Time Parameters
Transport Service V2	User Code V2
Version V3	Z-Wave Plus Info V2