

Z-Wave Protocol Implementation Conformance Statement

IQ Panel 2+

General Information

Product Identifier: QS9201-1208-840
Brand Name: Qolsys
Product Version: HW: 4 FW: 7.13:07.14:02.03
Z-Wave Certification #: ZC12-21060241

Product Features

Battery Type Lithium Ion

Z-Wave Product Information

Supports Z-Wave Beaming Technology? Yes
Supports Z-Wave Network Security? Yes
Supports Z-Wave AES-128 Security S0? Yes
Supports Security S2? Yes: S2 Access Control, S2 Authenticated, S2 Unauthenticated
SmartStart Compatible? Yes

Z-Wave Technical Information

Z-Wave Frequency: U.S. / Canada / Mexico
Z-Wave Product ID: 0x0004
Z-Wave Product Type: 0x0001
Z-Wave Hardware Platform: EFR32Z
Z-Wave Development Kit Version: 7.13.2
Z-Wave Library Type: Bridge Controller
Z-Wave Device Type / Role Type: Gateway / Central Static Controller

Association Group Information

Group # / Max	Description
Nodes	
1 / 5	Z-Wave Plus Lifeline

Z-Wave Protocol Implementation Conformance Statement

(Continued)

IQ Panel 2+

Supported Command Classes (24):

Application Status	Association Group Information V3
Association V2	CRC16 Encapsulation
Device Reset Locally	Firmware Update Meta-Data V5
Inclusion Controller	Indicator V3
Manufacturer Specific V2	Multi-Channel Association V3
Multi-Command	Network Management Basic V2
Network Management Inclusion V3	Network Management Proxy V2
Node Provisioning	Powerlevel
Security S0	Security S2
Supervision	Time
Transport Service V2	Version V3
Z/IP V5	Z-Wave Plus Info V2

Controlled Command Classes (24):

Association Group Information V3	Association V2
Barrier Operator	Basic V2
Battery	Central Scene V3
CRC16 Encapsulation	Door Lock V4
Firmware Update Meta-Data V5	Indicator V3
Manufacturer Specific V2	Meter V5
Multi-Channel Association V3	Multi-Channel V4
Notification V8	Security S0
Security S2	Sensor Multilevel V11
Thermostat Fan Mode	Thermostat Fan State
Thermostat Operating State	Thermostat Setpoint
Version V3	Wake Up V2