

Z-Wave Protocol Implementation Conformance Statement

2 Wire Dimmer

General Information

Product Identifier:	PAD15-US
Brand Name:	Philio
Product Version:	HW: 1 FW: 1.01
Z-Wave Certification #:	ZC12-21070272

Product Features

Color	White
Firmware Updatable	Updatable by Consumer by RF

Z-Wave Product Information

Supports Z-Wave Beaming Technology?	Yes
Supports Z-Wave Network Security?	Yes
Supports Z-Wave AES-128 Security S0?	Yes
Supports Security S2?	Yes: S2 Authenticated, S2 Unauthenticated
SmartStart Compatible?	Yes

Z-Wave Technical Information

Z-Wave Frequency:	U.S. / Canada / Mexico
Z-Wave Product ID:	0x007e
Z-Wave Product Type:	0x0005
Z-Wave Hardware Platform:	ZGM130
Z-Wave Development Kit Version:	7.13.5
Z-Wave Library Type:	Enhanced 232 Slave
Z-Wave Device Type / Role Type:	Multilevel Switch / Always On Slave

Association Group Information

Group # / Max	Description
Nodes	
1 / 5	1. Grouping 1 Lifeline (Maximum 5 nodes). 2. MULTILEVEL_SWITCH_REPORT When "on" or "o" state has been changed, it will send Multilevel Switch Report to the nodes of Grouping 1. 3. NOTIFICATION_REPORT

Z-Wave Protocol Implementation Conformance Statement

(Continued)

2 Wire Dimmer

Supported Command Classes (18):

Association Group Information V3

Basic V2

Device Reset Locally

Indicator V3

Multi-Channel Association V3

Powerlevel

Security S2

Switch Multilevel V4

Version V3

Association V2

Configuration V4

Firmware Update Meta-Data V5

Manufacturer Specific V2

Notification V8

Security S0

Supervision

Transport Service V2

Z-Wave Plus Info V2